PLC-XU355

XGA Ultraportable Multimedia Projector



A SIMPLE WIRELESS SETTING FOR USE WITH A USB MEMORY

The PLC-XU355 has an innovative wireless feature called "Simple Wireless Set Up". This model can set up a wireless connection easily without installing a software from a CD-ROM. Just pass off the USB memory. By connecting the PC and USB memory, the program in the PLC-XU355 starts running automatically, and the image will be projected directly on the screen.

NETWORKING CAPABILITY

Bright 3500Im, the PLC-XU355 is equipped with SANYO's exclusive PJ-Net Master Network Interface software for wired and wireless networking, a common feature among SANYO's extensive line of commercial projectors. Networking allows the monitoring of projector functions and operation from a long distance via a web browser for up 15,000 Sanyo projectors. Emails can be sent automatically to report operating status.

COMPLETE EASY AUTO SET UP FUNCTION, SMART AUTO INPUT SEARCH AND AUTO VERTICAL KEYSTONE CORRECTION

PLC-XU355 provides "Auto Set Up Function" that corrects keystone shaped distortion by searching for an input signal and detecting projector incline, therefore reducing set up time. PLC-XU355 automatically compensates for keystone picture distortion. Auto Keystone Correction, Auto Input Search and Auto PC Adjustment make it a really smart projector.

SHORT THROW LENS WITH 1.6 ZOOM AND 7W SPEAKER

PLC-XU355 is equipped with a zoom lens that allows screen size adjustment. The optical zoom works to maintain the image quality. The short-focus type lens allows large screen image projections with a short throw distance. The PLC-XU355 enables 100-inch screen projection at the shortest distance, 94 inches. Along with its mobility, the PLC-XU355 features a high-output 7 Watt speaker. Sufficient audio is delivered through its built-in speaker, so the projector can be used in conference rooms, classrooms, and other similar spaces.

BLACK BOARD / COLOR BOARD MODE

What could be more right for education? A black board mode. The PLC-XU355 is compatible with four colored (red, blue, green and yellow) projection surfaces via the 'Color Board Mode'. It adjusts the color to make images look as true as on an ordinary white screen.

LAMP REPLACEMENT ON TOP CABINET

There is access to the lamp from the top of the projector which means you can replace the lamp on a ceiling-mounted unit without taking down the projector.





PRESENTATION TECHNOLOGIES 21605 Plummer Street Chatsworth, CA 91311 Ph: 888-337-1215 (toll-free) Fax: 818-717-2719 www.sanyoprojectors.com

		cifications
Resolution		XGA (1,024 x 768)
Brightness (typical)		3500 Alm
Uniformity		85%
Panel System		0.63" TFT Polyx3
Number of Pixels		2,359.296 (786,432 x3)
Contrast Ratio (Full on / off)		500:1
Image Size		30"-300"
Aspect Ratio		4:3
Projection Lamp (s)		225W UHP
Scanning Freq		H:15-100kHZ, V:50-100Hz
Dot Clock	<u> </u>	140MHz
Fan Noise		29dBA(Eco) 34dBA(Normal)
Voltage		100-240V
BTU Rating		1,126 (Normal) 860W(Eco)
Power Consumption		330W (Normal) 252W(Eco)
Input signal compatibility Color System		UXGA / WXGA / SXGA+ / SXGA / XGA / SVGA / VGA /
		MAC, 480i / 480p / 575i / 575p / 720p / 1080i
		NTSC / PAL / SECAM / NTSC4.43 / PAL-M / PAL-N
Projection Lens (inch)		F1.65 – 2.33 f=0.61" - 0.97"
Throw Ratio		1.18-1.91:1
Throw Distance (feet)		2.26' - 23.72'
Zoom / Focus	0 (1000)	Manual
Zoom Ratio		1:1.6
Up / Down Ratio		9:1
Digital Keystone Correction		V +/- 30° (Auto Keystone)
Projection System		Diachronic mirror & X prism system w/PBS
Digital Zoom		16x - 1/4x
Speaker Output		7W
Weight (lbs.)		6.4 lbs
Dimensions (inch) W,H,D		
Dimensions (i	nch) W H D	12 8" x 3 3" x 9 1"
		12.8" x 3.3" x 9.1" 610 343 2069
Replacement I	Lamp	610 343 2069
Replacement I Replacement I	Lamp Remote	610 343 2069 645 099 3220
Replacement I	Lamp	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB)
Replacement I Replacement I	Lamp Remote PC1	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo)
Replacement I Replacement I	Lamp Remote	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog)
Replacement I Replacement I	Lamp Remote PC1	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo)
Replacement I Replacement I	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video)
Replacement I Replacement I	Lamp Remote PC1	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video)
Replacement I Replacement I INPUT	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono)
Replacement I Replacement I	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out)
Replacement I Replacement I INPUT	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable)
Replacement I Replacement I INPUT	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port)
Replacement I Replacement I INPUT	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control)
Replacement I Replacement I INPUT	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-I x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN)
Replacement I Replacement I INPUT OUT PUT CONTROL	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer)
Replacement I Replacement I INPUT OUT PUT CONTROL	Lamp Remote PC1 PC2	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS	Lamp Remote PC1 PC2 VIDEO	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-3 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord,
Replacement I Replacement I INPUT OUT PUT CONTROL	Lamp Remote PC1 PC2 VIDEO	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15 – Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer &
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS	Lamp Remote PC1 PC2 VIDEO	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS	Lamp Remote PC1 PC2 VIDEO	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15-Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap,
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS Included Acces	Lamp Remote PC1 PC2 VIDEO	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini JIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap, Storage case for USB memory
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS Included Access Optional Access	Lamp Remote PC1 PC2 VIDEO Ssories	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini JIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap, Storage case for USB memory POA-CACOMPVGA (component-Dsub 15 conversion Cable)
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS Included Acces	Lamp Remote PC1 PC2 VIDEO Ssories	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini JIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap, Storage case for USB memory POA-CACOMPVGA (Component-Dsub 15 conversion Cable) Clean air filters, replace lamp assembly
Replacement I Replacement I INPUT OUT PUT CONTROL OTHERS Included Access Optional Access	Lamp Remote PC1 PC2 VIDEO Ssories	610 343 2069 645 099 3220 Dsub-15 x 1 (RGB, Component, RGB) Mini jack x 1 (Audio input, stereo) DVI-1 x 1 (Digital & Analog) Mini jack x 1 (Audio input, stereo) Mini JIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-8 x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap, Storage case for USB memory POA-CACOMPVGA (component-Dsub 15 conversion Cable)

Because its products are subject to continuous improvement, SANYO reserves the right to modify product design and specifications without notice and without incurring any obligations.



Rear Back Panel